

**Table 3: NPR Test Results, FTDX-3000 S/N 2K020095, 3 Mar. 2013. VA7OJ.**

DUT	BSF kHz	BLF kHz	Preamp	MDS dBm	P <sub>TOT</sub> dBm	BWR dB	NPR dB
FTDX-3000	1940	60...2044	0	-121	-16.2	29.2	75.3
			1	-133	-27.4		76.0
			2	-135	-30.2		73.3
	3886	60...4100	0	-120	-14.6	32.3	72.8
			1	-132	-29.4		69.0
			2	-135	-31.8		70.6
	5340	60...5600	0	-119	-12.7	33.6	72.4
			1	-131	-27.3		69.8
			2	-134	-30.5		66.6
	7600	316...8160	0	-119	-14.2	35.1	69.4
			1	-131	-29.1		72.5
			2	-134	-31.2		73.4

**BSF:** Bandstop (Notch) Filter. **BLF:** Band Limiting (Bandpass) Filter.