

**Table 2: NPR Test Results, IC-7600 # 0202881. 28 May 2012. VA7OJ.**

DUT	BSF kHz	BLF kHz	Config	MDS dBm	P <sub>TOT</sub> dBm	BWR dB	NPR dB
IC-7600	1940	60...2044	Preamp off R15	-124	-15	29.2	75.3
			R6		-14.7		78.8
			R3		-14.7		78.8
			Preamp 1 R15	-132	-20		82.5
			R6		-20		82.5
			R3		-20.2		82.3
			Preamp 2 R15	-133	-23.3		80.2
			R6		-22.3		81.2
			R3		-23.6		79.9
	3886	60...4100	Preamp off R15	-124	-10.6	32.3	80.8
			R6		-10.4		78.8
			R3		-10.5		78.8
			Preamp 1 R15	-132	-20		79.3
			R6		-18.8		80.6
			R3		-19.2		80.2
			Preamp 2 R15	-133	-23.3		80.1
			R6		-22.7		77.7
			R3		-23.3		77
	5340	60...5600	Preamp off R15	-124	-10.1	33.6	80
			R6		-10.2		79.9
			R3		-10.8		79.2
			Preamp 1 R15	-132	-19.8		78.3
			R6		-19.5		78.6
			R3		-19.7		78.4
			Preamp 2 R15	-134	-24.5		75.6
			R6		-24.2		75.9
			R3		-24.4		76.1
	7600	316...8160	Preamp off R15	-124	-9.6	35.1	79
			R6		-9.7		78.9
			R3		-9.8		78.8
			Preamp 1 R15	-132	-18.9		77.7
			R6		-18.8		77.8
			R3		-19.1		77.5
			Preamp 2 R15	-134	-24.3		74.3
			R6		-24.2		74.4
			R3		-24.2		74.4
<b>BSF: Bandstop (Notch) Filter.</b>			<b>BLF: Band Limiting (Bandpass) Filter.</b>				